



## How to Connect Your Promethean Chromebox to Your ActivPanel Nickel

To connect your Promethean Chromebox to your ActivPanel Elements Series, begin by ensuring you are running the most up-to-date firmware. Please visit [support.prometheanworld.com/update](https://support.prometheanworld.com/update) and/or [support.prometheanworld.com/article/1744/](https://support.prometheanworld.com/article/1744/) for more information.


Connect your HDMI and USB cables to the **HDMI 2** and **USB 2** ports.




Plug in the power cable and power your Chromebox **on**. You will also need a Google account.




Access the **Unified Menu** and tap **Source**. Select **HDMI2** to switch over to your Chromebox.






Tap in the **bottom right** of the Chromebox desktop to access some basic settings. You will want to ensure your ActivPanel and Chromebox are connected to the same internet network.



You may need to log into your Google account at this point. Go to the Google Play Store to locate and install the **Promethean Chromebox Utility App**.




Next, locate your ActivPanel's serial number by opening the **Unified Menu**, then the **Locker**. Select the **Update** icon from the Apps tab in the Locker. Make note of the serial number which is found at the bottom left corner of the Update window.

# Promethean®


Open the **Unified Menu** once more and tap **Source**, then select **HDMI2** to return to the Chromebox.

Tap to open the **Chromebox notification area** at the bottom right of the screen. There will be two notifications.


One notification will say “Please enable usage access by clicking here” and the second will say “Click to Set Panel Serial number.” To enable usage access, tap “**Please enable usage access by clicking here.**”




Once you tap the notification, you will be taken to a Usage Access settings screen. Select **Promethean Chromebox Utility**.




On the next screen, toggle the Panel usage access **ON**.



Next, tap the “**Click to Set Panel Serial number**” notification. You will be presented with a dialog box. Enter the ActivPanel’s serial number and tap **OK**. The serial number is not case sensitive.



You should now see a message that the Promethean Chromebox Utility has connected to an IP address, signifying that the Chromebox and the ActivPanel are now connected.



You can check the status of the connection to your panel at any time by tapping on the **notification area** at the bottom right of the Chromebox desktop and the Promethean Chromebox Utility app will show it is connected.

From now on, all apps from your Promethean Chromebox will appear within your Locker for easy access.

For more information or to receive assistance, please visit [support.prometheanworld.com](https://support.prometheanworld.com).

Follow us on Twitter [@LearnPromethean](https://twitter.com/LearnPromethean), subscribe to our [Promethean Video](#) YouTube channel, [sign up](#) to hear from us, and [visit our website](#) to learn more.

